

# BE 2k

## A.M.F. Generating Set Controller

State-of-the-art generating set controller



The Be2K is a high performance 3-phase A.M.F / Generator controller and monitoring system. It displays all parameters involved in the automation of a Generator. A serial interface Rs232 or RS485-MODBUS, is provided for Modem and Remote control. This software allows you to program, monitor and calibrate measurements. The Be2k can be easily controlled by Mobile Phones, using the Be15 option. The Be15 also provides 15 additional programmable relay outputs. A Windows XP (\*) compatible control and monitoring software is provided.

### Key features :

- Powerful set of 70 input-output lines
- 80 programmable parameters & real-time clock
- 3-Phase Generator & Mains monitoring
- RS232/485 that includes MODBUS
- Local or Remote operating modes selection
- 21 Operating and 60 Alarm Messages
- Event Logging, scheduled maintenance programs
- Programmable timeout for RENTING applications

### Front Panel features:

- 21 LEDs, 13 Pushbuttons, 4 Displays
- Aac, Vac, Hz, Vdc, kVA, kW, kVAr and PF indications
- BAR, Temperature, % Fuel, RPM and h-meter
- All measurements may be calibrated on field when engine is running

### Miscellaneous features:

- Temperature Range -30° / +70°C
- IP 54 protection grade
- Outdoor/Indoor operation
- Panel Cut-out: 171x238
- Dimensions: 250x185x70 / 1700gr.
- Supply Range up to 36Vdc, max 300mA

\* Windows is a registered trademark of Microsoft Corporation

Bernini Design srl  
via S.Romano Casetto 26/A  
46035 OSTIGLIA (Mn) Italy  
tel. ++39 386 31445  
fax ++39 386 31657  
[www.bernini-design.com](http://www.bernini-design.com)

**BERNINI**  
design

Visit our web site to find your nearest distributor